## **Model Name:**

### **Basic PDU**

### **Features:**

### **Power Management:**



### **Overload Protection**

When overload, circuit breaker will automatically trip to protect the safety of electricity.

### Power Management Upgrade: (Works with CPM, the following are CPM functions)



### **Remote Monitor**

Remote monitoring PDU status by web and SNMP



### **Threshold Sensing**

User-definable warning and overload threshold value as the basis for alarm.



### **Environment Detection**

Optional accessory probe to detect temperature and humidity. (available by model)



### **Mail Notification**

Notify specified user by mail and SNMP when outlet action or current over threshold.



MANAGEMENT

### **Central Management**

Free centralized monitoring software, real-time monitoring of a large number of PDU, provide data records and history chart.

# **Model Number:**

# B1H-2011B-08N1





# **Specification**

Output		Input	
Voltage	100-127 VAC	Voltage	100-127 VAC
Max. Current	20 A	Frequency	50/60Hz, full range
Outlet	(8) 5-15/20R	Max. Capacity	2540 VA
Overload Protection	(1) 20A UL1077 breaker	Connection	5-20P, power cord, 3m
		Power Ind.	(1) Green LED
Measurement		Other	
None		CPM Link	(1) RJ11
		CPM Link Ind.	(1) Yellow LED
Dimension/Weight			
Dimension/Weig	ht	Operation	
<b>Dimension/Weig</b> l Net size	<b>ht</b> 432 x 44 x 44 mm	Operation Operation Temp.	0 ~ 45°C
, ,		•	0 ~ 45°C 0% ~ 90% RH
Net size	432 x 44 x 44 mm	Operation Temp.	-
Net size Net weight	432 x 44 x 44 mm 1.5 kg	Operation Temp. Operation Humid.	0% ~ 90% RH
Net size Net weight Package Size	432 x 44 x 44 mm 1.5 kg 505 x 210 x 90 mm	Operation Temp. Operation Humid. Storage Temp.	0% ~ 90% RH -20°C ~ 65°C
Net size Net weight Package Size Package Weight	432 x 44 x 44 mm 1.5 kg 505 x 210 x 90 mm	Operation Temp. Operation Humid. Storage Temp.	0% ~ 90% RH -20°C ~ 65°C

# **Package**

# No. Description. 1 PDU 1 set 2 Rack mount accessories 1 set

# **Optional Accessory**

Model Number	Model Name
CPM-MON- 08100-EX	CPM –Cabinet Power Monitor
	## 2

3 Manual by link below



# **Line Drawing**







