# **Model Name:**

# **Elite POM PDU**

Elite POM PDU provides remote manual control of the critical devices by clicking on a few buttons on the smart phone or computer webpage. Stop the problem device by cutting off the power to a specific outlet. By cycling the power off and restarting the device remotely, you save time and money by eliminating the need to send technicians to the root cause of the problem.

Managers can monitor the power usage information of each output port from the remote end through the Internet to fully understand the power consumption of all the devices. Set up overload event alerts and notify managers via Email and TRAP, allowing managers to respond to crises in the shortest possible time to minimize disasters.

The PDU has two environmental sensor ports that track climate information: temperature and humidity environment variables. The data is available from any web browser and is SNMP-compliant for easy tracking of critical data without the use of any external software.

Provide central management software, which can manage a large number of PDUs' power, temperature and humidity information. The database stores the power consumption information of the power strip and provides the history curve chart for the manager's reference.

# **Features:**

# **System Function:**

- Built-in embedded system:
   Support 10/100M Ethernet interface, provides webpage and SNMP remote management.
- Local display information:
   Seven-segments can display current, IP address and temperature and humidity values.
- Multiple protocols:
   Support ICMP, ARP, IP, TCP, UDP, DHCP, HTTP,
   HTTPS, FTP, NTP, SNMP v1/2/3, TLS1.2, IPv4 and
   IPv6, Telnet, SSHv2
- Management Account Certification: Radius certification support.
- Multi-account management: Multi-group account management system. And provide three-tier permission management.
- IP filtering: Support IP filtering, improve network security mechanisms.
- Power record: Store up to 100000 power and event data.

- Remote firmware upgrade:
   Provides remote firmware upgrade mechanism.
- System operation message:
   Send the normal operation of the message automatically by trap.
- Hardware key definition:
   User-definable button function.
- Temperature unit conversion: Temperature units can choose Celsius or Fahrenheit
- System configuration restore:
   Support the output of the system settings, to easily deploy a large amount of the same model of PDU.
- Multilingual Support:
   Support Chinese, English, French, German,
   Spanish, Russian, Czech, Arabian, Persian.

# **Power Management:**



REMOTE MONITOR

#### **Remote Monitor**

Remote monitoring PDU status by web and SNMP



REMOTE CONTROL

## **Remote Control**

Remote per outlet on/off by web and SNMP.



CURRENT MEASUREMENT

#### **Current Measurement**

Measure PDU total current consumption.



#### **Mail Notification**

**Event Alert** 

Notify specified user by mail and SNMP when outlet action or current over threshold.



# **Threshold Sensing**

User-definable warning and overload threshold value as the basis for alarm.



EVENT ALERT

M/h on ourre

When current exceeds the preset threshold, PDU will beep and LED will flash.



## **Power Sequence**

User-definable power on/off sequence time.



CONTROL

#### **Schedule Control**

Timed & scheduled on/off/reboot control.



PING EVENT CONTROL

## **Ping Event Control**

When the specified IT device does not respond to PING, the output will perform a preset power action.



PROTECTION

## **Overload Protection**

When overload, circuit breaker will automatically trip to protect the safety of electricity.



GROUP CONTROL

# **Group Control**

Set multiple outlets as a single group while controlling the power output.



# **Outlet-Level Monitor**

Remote per outlet current monitoring.



EVENT REACTION

## **Event Reaction**

Outlet action via pre-set event, including power, environment event and receiving trap from other device.



MANAGEMENT

## **Central Management**

Free centralized monitoring software, real-time monitoring of a large number of PDU, provide data records and history chart.



#### **Environment Detection**

Optional accessory probe to detect temperature and humidity.

# **Model Number:**

# MSD-2011B-08N8



# **Specification**

| <u>-                                      </u>   |  |  |  |
|--|--|--|--|
| Output   |  | Input  |  |
| Voltage Max. Current Outlet ON/OFF Ind. Outlet Status Ind. Circuit Status Ind. Overload Protection | 100-127 VAC 20 A (8) 5-15/20R (8) Green LED (8) Red LED (1) Red LED (1) 20A UL1077 breaker | Voltage<br>Frequency<br>Max. Capacity<br>Connection                                | 100-127 VAC<br>50/60Hz, full range<br>2540 VA<br>C20, Inlet  |
| Measurement  |  | Other  |  |
| Current  | +/- 2%+/-0.1A @0.2A ~ 32 A   | ENET Connection ENV Connection Function Selection DHCP Ind. SSL Ind. Info. Display | <ul><li>(1) RJ45</li><li>(2) RJ11</li><li>(1) Button</li><li>(1) Green LED</li><li>(1) Blue LED</li><li>4 digits of 7 Segments</li></ul> |
| Dimension/Weight   |  | Operation  |  |
| Net Size<br>Net Weight<br>Package Size<br>Package Weight   | 432 x 216 x 44.5 mm<br>3.8 kg<br>490 x 330 x 155 mm<br>4.4 kg                              | Operation Temp. Operation Humid. Storage Temp. Storage Humid.                      | 0 ~ 50°C<br>0% ~ 90% RH<br>-20°C ~ 65°C<br>0% ~ 90% RH   |
| Approval   |  |  |  |
| Certification<br>Warranty  | FCC<br>2 years   |  |  |

# **Package**

# No. Description 1 PDU 1 set 2 Rack mount accessories 1 set 3 C19 to 5-20P, power cord 3m 4 Software, manual, MIB by link below

# **Optional Accessory**



# **Line Drawing**

